


**MODEL AL2273-402****16 CHANNEL RS422  
OUTPUT MODULE****1 FEATURES**

- **High Signal Density with 16 RS422 Outputs per Card**
- **Industry-Standard Triax Connectors**
- **Maximum 30Mbps Operation**
- **On-board BERT logic for System Self-Test**
- **Supports AL2273 Standard Hot-Swapping**
- **Single Height AL2273 Input Module**

**2 PURPOSE**

The AL2273-402 16 Channel RS422 Output Module is an output card for use with the AL2273 Digital Matrix Switch that allows industry-standard RS422 output signal support up to 30Mbps. The card supports hot-swapping during normal operation to reduce system downtime, and incorporates a BERT function for system self-test.

### 3 SPECIFICATIONS

#### 3.1 RS422 OUTPUTS

- 16 Outputs, RS422 Compatible
- Expected Differential Load Impedance<sup>1</sup> : 100  $\Omega$
- Triax Output Connectors<sup>2</sup>
- Maximum Bit Rate: 30Mbps<sup>6</sup>
- Output Short Circuit Protection<sup>3</sup>
- Minimum Differential Output Voltage<sup>1</sup> : 2.0V

#### 3.2 TIMING PERFORMANCE

- Adjacent Channel Pair Propagation Delay Mismatch<sup>4</sup> : < 5ns
- Any Channel Pair Propagation Delay Mismatch<sup>4</sup> : < 10ns
- Maximum Propagation Delay<sup>4</sup> : < 15ns

#### 3.3 GENERAL

- Power Consumption: 15W<sup>5</sup>
- Operating Temperature: 0 °C to 50 °C
- Relative Humidity: 0 to 95%, Non-Condensing
- Chassis Slot Requirement: Single

**Notes:**

- (1) Standard RS422 termination is 100 $\Omega$ , floating resistive load
- (2) Connector is a Trompeter BJ770GL
- (3) Rated for continuous fault condition
- (4) Measured from differential LVDS pair on backplane connector to output terminated in 100 $\Omega$
- (5) Rated with all outputs driving 100 $\Omega$  load at 30MHz, 50% duty cycle
- (6) Specified NRZ-L

Apogee Labs Inc. products are sold by description only. Apogee Labs Inc. reserves the right to make changes in circuit design, software, hardware, and/or specifications at any time without notice. Although Apogee Labs Inc. believes that the information provided is current and accurate, Apogee Labs Inc. does not assume any responsibility or liability for the use of any product described. It is the responsibility of the user to determine appropriate use of the product in any given application.